

GATEKEEPER E2

4MM FIXED LENS · 5 MEGAPIXEL · 7 DAY ONBOARD RECORDING



NIGHT
VISION



7 DAY ONBOARD
RECORDING



MOTION
SENSING



WEATHER PROOF
METAL CASING



Monkey Vision
**ARE THE ONLY CAMERAS
DESIGNED IN AUSTRALIA
AND OPTIMISED TO WORK
BETTER IN AUSTRALIA.**

TECHNICAL SPECIFICATIONS

GATEKEEPER E2

CONNECTIVITY

Connectivity	PC & Mobile
4G	No
WiFi	No
Streaming Method	Unicast/Multicast

OPTICS

Lens	4.0mm
Field of View	87.5°
Image Sensor	1/2.8 CMOS
Optical Zoom	N/A
Focus Control	Auto/Manual
Close Focus Distance	100mm ~ ∞
Shutter Speed	Variable (1H units)
Scanning System	Progressive
Aperture	F1.6
Minimum Illumination	0.59lx @ F5.6 night

IMAGE

Megapixel	5
Video Compression	H.265
Streaming Capability	2 Streams
Resolution	2560P/1080P/720P
Frame Rate	1-25fps
Bit Rate	32-6144/32-2048
Bit Rate Control	CBR/VBR
Noise Reduction	Ultra DNR
ONVIF	YES

CAMERA

Model Number	GKE2
Product Name	Gatekeeper E2
Onboard Memory	64GB
Pan	N/A
Tilt	N/A
Presets	N/A
Event Trigger	Motion Detection with Focus
Advanced Intelligent Features	Human Detection
Casing	Metal
Ingress Protection	IP66
Day/Night	Auto (ICR)/Colour/B&W
External Speaker	N/A
Microphone	Built-in
Power Supply	12V/1A DC
Power Consumption Day/Night	5W/10W
Operating Conditions	-20°C~+60°C
Signal to Noise Ratio	69dB
IR Distance	Up to 30m
IR On/Off Control	Auto/Manual







MONKEY VISION



www.monkey-vision.com.au/

HOW TO VIEW, DOWNLOAD AND SHARE FOOTAGE

- 1** OPEN THE MONKEY VISION CONNECT APP. 
- 2** TAP THE VIDEO BUTTON AT THE BOTTOM OF THE SCREEN, THEN SELECT ONLINE AT THE TOP OF THE SCREEN. 
- 3** SELECT THE CAMERA YOU WISH TO VIEW FROM YOUR LIST. 
- 4** YOU CAN SEE ALL FOOTAGE WITHIN AN HOUR, DAY, OR WEEK. TO SELECT A SPECIFIC DATE & TIME, TAP THE SEARCH ICON (TOP RIGHT) AND CHOOSE 'CUSTOM'. 

- 5** CHOOSE TO   PLAY OR DOWNLOAD THE FOOTAGE.
- 6** ONCE YOUR VIDEO HAS DOWNLOADED, CHOOSE TO KEEP DOWNLOADING OR GO TO SEE TO GO DIRECTLY TO WHERE THE VIDEOS HAVE BEEN SAVED. 
- 7** TAP THE EXPORT ICON TO CONVERT THE FOOTAGE TO MP4 VIDEO. 
- 8** THE VIDEO WILL APPEAR IN YOUR DEVICE'S PHOTO GALLERY. 











MONKEY VISION



www.monkey-vision.com.au/

HOW TO SET VIDEO ALARMS ON THE CONNECT APP

- 1** Open the Monkey Vision Connect app and TAP THE SETTING ICON for the camera you want to set up 
- 2** TAP ALARM SETTING > 
- 3** ACTIVATE MOTION DETECTION 
- 4** FOLLOW THE PROMPTS TO SELECT AN AREA TO MONITOR 
- 5** TAP APPLY THEN < BACK 
- 6** TAP ACTION WITH ALARM > 
- 7** ACTIVATE ALARM NOTIFICATIONS ALARM SD REC 
- 8** TAP < BACK TWICE TO RETURN TO YOUR CAMERA LIST 



MONKEY VISION

SETTING YOUR TIME ZONE



www.monkey-vision.com.au/

- 1 OPEN THE MONKEY VISION CONNECT APP



- 2 TAP THE SETTINGS ICON NEXT TO YOUR CAMERA



- 3 SCROLL DOWN AND TAP ON TIME SETTING >

- 4 TAP SYNC WITH PHONE TIME SO YOUR PHONE AND CAMERA DON'T ARGUE OVER WHAT TIME IT IS

- 5 CHOOSE YOUR TIME ZONE - A DROP DOWN MENU WILL APPEAR WHEN YOU TAP



DEVICE TIME ZONE

- 6 SLIDE THE DAYLIGHT SAVING TIME TAB INTO THE ON POSITION



- 7 TAP SAVE TIME ZONE FOR DEVICE TAP <BACK TWICE TO RETURN TO YOUR CAMERA LIST



MONKEY VISION

POE QUICK SET-UP GUIDE



www.monkey-vision.com.au/

- 1 CABLES. Run a Cat6 ethernet cable from your PoE switch out to where you want to install the camera.



- 2 CONNECT. Connect the camera to the cable and secure to your ceiling or eave.



- 3 SCAN & GO



Then, scan the UID to add your camera.

- 4 OPEN THE APP. Tap the bar.



- 5 Give your camera a NAME. Be funny. Be relevant. It's up to you. Leave the username as 'admin' and don't change the password just yet.



- 6 TAP THIS



Then scan this sticker on your camera



and then tap on the tick at the top right of the app



- 7 TAP THE SETTING ICON NEXT TO YOUR CAMERA.

Go to Change password to change your password. (duh)

- 8 SCREW IT UP AND YOU'RE ALL DONE!

